

BC14 Spares

Backup Battery Storage

FEATURES:

- ▶ Standard 115/130 VAC hardwire input
- ▶ Other charger inputs are available
- ▶ Max Current: 6.6A @ 120VAC
- ▶ Internal 12V, 10A charger
- ▶ Standard 5-15P input cord
- ▶ Batteries are pre-installed
- ▶ Wired with fused, pluggable connectors
- ▶ Heavy duty casters with elevator bolts
- ▶ Multiple battery configurations
- ▶ Available in multiple powder coat finishes
- ▶ Zone 4 approved



C&CPower's BC14 spares battery cabinet is a convenient solution for storing spare batteries on site. The cabinet consists of a 12 volt charger inside that is pre-wired to the batteries with pluggable connectors.

The charger keeps the batteries fully charged and allows for immediate replacement into critical systems. This NEMA 1 rated battery cabinet is constructed of welded, heavy gauge steel and is available in multiple colors of durable and corrosion resistant, powder coat finish.

Battery Configurations			
	WPC Capacity	Max. # of batteries	Weight
TOP TERMINAL	150W	20	885 lbs
	200W	15	890 lbs
	300W	8	725 lbs
	350W	8	815 lbs
	400W	6	725 lbs
	500W	6	865 lbs
	540W	6	885 lbs