

# BC25 Spares

## Backup Battery Storage




### FEATURES:

- ▶ Standard 115/130 VAC hardwire input
- ▶ Max Current: 5.6A @ 115 VAC/2.8A @230 VAC
- ▶ Internal 12 VDC charger
- ▶ Optional input cord available
- ▶ Batteries are pre-installed with pluggable connectors
- ▶ Heavy duty casters with elevator bolts
- ▶ Multiple battery configurations
- ▶ Available in multiple powder coat finishes
- ▶ Zone 4 approved
- ▶ Seismic certified options available

**C&C**Power's BC25 Spares Battery cabinet is a convenient solution for storing spare batteries on site. The cabinet consists of a 12 volt charger inside that is pre-wired to the batteries with pluggable connectors.

The charger keeps the batteries fully charged and allows for immediate replacement into critical systems. This NEMA 1 rated battery cabinet is constructed of welded, heavy gauge steel and is available in multiple colors of durable and corrosion resistant, powder coat finish.

### OPTIONAL CONFIGURATION:



	Battery Configurations		
	WPC Capacity	Max. # of batteries	Weight
TOP TERMINAL	200W	30	1565
	300W	24	1715
	350W	24	1980
	400W	24	2120
	500W	16	2023
	540W	16	2071
	620W	16	1991
FRONT ACCESS	100AH	10	1175
	150AH	10	1575
	170AH	10	1875