

Maintenance Bypass

90885 Series Wall Mount Breaker Panel

FEATURES:

- ▶ Available in 10K AIC rating
- ▶ Three breaker design (15A-225A)
- ▶ 22-inch wide wall mount design
- ▶ Compact design minimizes footprint
- ▶ Multiple system configurations



C&C Power's 90885 Wall Mount Maintenance Bypass Breaker Panel is our *most economical option for low AIC applications*. It's available in multiple configurations and allows the end user to safely isolate the UPS from utility power and from the load to perform regular service and maintenance. The MBBC contains three Cutler Hammer Series C circuit breakers that are protected by a Kirk Key interlock system that comes standard on every configuration.

Our 90885 wall mount bypass panel is available at 10k AIC for 480V and 208V 3-phase applications. It's also available in a 120/240 VAC single phase configuration.

SPECIFICATIONS:

Voltages:	120/240 VAC, 1-Phase, 3-Wire 208Y/120 VAC, 3-Phase, 4-Wire 480Y/277 VAC, 3-Phase, 4-Wire
Operating Temp:	0° to 40° C (32° F to 104° F)
System Capacity:	15-225 Amperes
Ac Input/Output Terminations:	Mechanical lugs are used for both
Wire Size and Type:	Per NEC and/or all applicable national and local codes

Specifications		
Style	Dimensions	Weight
90885	22"W x 24"H x 9"D	55 lbs