

Landing Box

Battery Cabinet Accessory



FEATURES:

- ▶ More power in less space
- ▶ Parallel multiple battery cabinets
- ▶ BC55, UBC64, and UBC75 compatible
- ▶ Multiple copper configurations
- ▶ Welded, heavy gauge steel construction
- ▶ Available in multiple powder coat finishes

C&CPower's Landing Boxes provide a convenient means for paralleling multiple battery cabinets. Landing Boxes are provided with landings for two hole compression lugs for battery positive, battery negative, and ground. A circuit breaker accessory terminal block is also provided.

Landing boxes are available for use with C&C Power's BC55, UBC64, and UBC75 battery cabinets.



Landing Box Configuration Table				
Style	Dimensions	Weight	Current Capacity	Cabinet Compatibility
95401-15	40.0"W x 30.0"H x 20.0"D	140 lbs	1500A	BC55
95401-30	40.0"W x 30.0"H x 20.0"D	167 lbs	3000A	BC55
95401-45	40.0"W x 30.0"H x 20.0"D	195 lbs	4500A	BC55
95402-15	43.3"W x 30.0"H x 21.5"D	145 lbs	1500A	UBC64 / UBC75
95402-30	43.3"W x 30.0"H x 21.5"D	172 lbs	3000A	UBC64 / UBC75
95402-45	43.3"W x 30.0"H x 21.5"D	200 lbs	4500A	UBC64 / UBC75